

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE  
GENERATORS**

ESTABLISHED 1949

POWERED by  
**HONDA**™

# Honda 12V 80A Outback Battery Charger (GX10080ND)

This 12 volt 80 amp Battery Charger is powered by a genuine Honda 100cc 4-stroke engine. Manual 2 stage charge rate, Low 14V or high 14.6V charge rate, by the flick of a switch. Lightweight, portable, weighing only 22 kg. High current Leads included, 3m long with large heavy-duty alligator clamps.

## IDEAL FOR

- Ideal for charging up to 2- N70 cranking batteries at once
- Farmers can supply enough charge in as little as 5 minutes to start any machinery
- Run car fridges for 24 hours and charge your batteries in as little as 1 hour
- 12 Volt lighting or other appliances can be powered in emergency situations
- Ideal for the marine industry, backup for solar powered sites, emergency services, earthmoving contractors, mobile mechanics, or anyone working in the outback

Note, some deep cycle batteries will not accept a fast charge & may require trickle charging for a long period of time.



## FEATURES

- Low or High charge rate, by the flick of a switch
- Short circuit and Over voltage protected
- Super bright LED charge indicator
- Lightweight, portable, weighing only 22 kg
- High current Leads included, 3m long with heavy-duty alligator clamps
- 3 Years Engine Warranty

Environmentally friendly  
OHC Honda 100cc



Proudly Made in  
Australia!

### MELBOURNE

136 Fairbank Road  
Clayton South, VIC 3169  
(03) 9544 4222

### SYDNEY

1 St James Place  
Seven Hills, NSW 2147  
(02) 9899 6699

### BRISBANE

31 South Pine Road  
Brendale, QLD 4500  
(07) 3205 6333

# Specifications

Model	GX10080ND
Weight	22kg
Dimensions LxWxH (mm):	465 x 330 x 470
Engine:	Honda GX100 air cooled
Alternator:	Bosch 80 amp
Max eng. power:	3hp@3600rpm
Fuel capacity:	1.2 Litres
Fuel type:	4-stroke unleaded petrol
Fuel consumption:	Approx. ¾ Litres / hour
Oil capacity:	0.4 Litres
Starting system:	Recoil
Electric output:	12 Volts D.C.
Max voltage (low):	14 Volts regulated
Max voltage (high):	14.8 Volts regulated
Max amp output:	80 Amps
Voltage cut out:	18 Volts

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE  
GENERATORS**

ESTABLISHED 1949

POWER ANYWHERE, ANYTIME!

**1300 MAC GEN (1300 622 436)**

[www.macfarlanegenerators.com.au](http://www.macfarlanegenerators.com.au)

[info@macgen.com](mailto:info@macgen.com)

**MELBOURNE**

136 Fairbank Road  
Clayton South, VIC 3169  
(03) 9544 4222

**SYDNEY**

1 St James Place  
Seven Hills, NSW 2147  
(02) 9899 6699

**BRISBANE**

31 South Pine Road  
Brendale, QLD 4500  
(07) 3205 6333