

POWERLINK EP Perkins Series Diesel Generator with Leroy Somer Alternator



Model: **WPS1000S-AU**
 Frequency: **50Hz**
 Fuel type: **Diesel**
 Powered by: **PERKINS SERIES**

415/240V-50Hz-3Phase

- Powerful heavy-duty Perkins industrial diesel and low emissions engine
- Intelligent control - Manual & Remote start
- Weather protective and sound attenuated enclosure
- Comprehensive warranty and service

TECHNICAL SPECIFICATIONS

Model	WPS1000S-AU			
Power(ESP)	kVA/kw	1100/880		
Power(PRP)	kVA/kw	1000/800		
Voltage	V	415/240		
Fuel Consumption	Litres/hour	Fuel consumption100% (of the Prime Power)	215 L/h	
		Fuel consumption75% (of the Prime Power)	162 L/h	
		Fuel consumption50% (of the Prime Power)	111 L/h	
		Fuel consumption25% (of the Prime Power)	N/A	
Fuel Tank Capacity	Litre	1150		
Noise Level	dB(A)@7m	79.6dBA		
Dimensions and Weight	Length	Width	Height	Weight
	6058 mm	2438 mm	2591 mm	11570 kg

ENGINE SPECIFICATIONS

Manufacturer	Perkins
Model	4008-TAG2
Engine Speed Rated	1500 RPM
Cylinder /Arrangement	8
Displacement	30 L
Bore and Stroke	160 mm x 190 mm
Compression Ratio	13.6
Intake Resistance	≤3.7kPa
Governor Type	Direct injection, Turbocharged
Total Oil Capacity w/Filters	153 L
Coolant Capacity	149 L

PROUDLY 100% AUSTRALIAN OWNED


**MACFARLANE
GENERATORS**
ESTABLISHED 1949

Power Anywhere Anytime | WPS1000S-AU | 11.2024

MACFARLANEGENERATORS.COM.AU

ALTERNATOR SPECIFICATIONS

Manufacturer	Leroy Somer LSA49.3L10
Phase	3
Power Factor	0.8
Bearing	1
Exciter type	Brushless
Insulation : Class , temperature rise	H
Degree of protection	IP23
AVR model	R250
Altitude	≤1000m
Winding Pitch	2/3
Overspeed	2250rpm



AIR SYSTEM

Engine Air Flow	1.614m ³ /s(50Hz)
-----------------	------------------------------

Note: All data sheets are for reference only and subject to change without prior notice.

CONTROL PANEL

ComAp	IntelliLite 4 AMF9
-------	--------------------

KEY FEATURES

- Easy configuration with IntelliConfig
- Remote monitoring
- Cybersecurity by design
- Easy troubleshooting
- Built-in PLC logic
- Flexible platform
- Stand-by and prime power application control
- Zero power mode
- Secure user management



PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE
GENERATORS**

ESTABLISHED 1949

POWER ANYWHERE ANYTIME

MELBOURNE | SYDNEY | BRISBANE

www.macfarlanegenerators.com.au | info@macgen.com
SALES | SERVICE | SPARES | HIRE | NEW | USED