



9kVA Maxwatt Electric Start **Inverter Generator**

PORTABLE & LIGHT WEIGHT 2-WIRE AUTO START | LOW NOISE 76DB

The Maxwatt® range of generators have been manufactured using only high-quality components and designed to last in the toughest conditions.

Maxwatt MX11000i with 2-wire auto start generator has been designed to provide backup power for off-grid solar systems. It has a pre-installed 2-wire automatic control system. This generator can automatically provide backup to recharge the storage battery and feed -in power to supply the load.

Besides the electrical output being able to power all sensitive equipment, the MX11000i is perfect for worksites, as well as emergency home backup power.

















FEATURES

- Electric Starting System Battery Included
- Pure Sine Wave Power for Sensitive **Electronic Appliances / Devices**
- 4 Stage Digital Meter Display
- Superior SENCI Alternator
- Compact and Easy to Transport

MELBOURNE

136 Fairbank Road Clayton South, VIC 3169 (03) 9544 4222

SYDNEY

1 St James Place Seven Hills, NSW 2147 (02) 9899 6699

BRISBANE

31 South Pine Road Brendale, QLD 4500 (07) 3205 6333

Specifications

Model	MX11000i
Power Maximum	9000W
Power Rated	8500W
Voltage	240V
Amperage	35.4A
Outlets	1 x 15 Amp IP44, 1 x 15 Amp IP66, 1 x 32 Amp IP66
Displacement	459cc
Ignition	Electric / Remote Control
Rated Frequency	50Hz
Cont. Running Time @50% Load	16hrs
Cont. Running Time @100% Load	11hrs
Fuel Tank Capacity	34L
Noise Level (dB @ 75% m)	76
Total harmonic distortion (THD)	<3%
Weight (kg)	78kg
Dimensions (LWH)	708 x 550 x 656mm
Manufacturer's Warranty	2 year warranty



POWER ANYWHERE, ANYTIME! 1300 MAC GEN (1300 622 436)

www.macfarlanegenerators.com.au info@macgen.com

MELBOURNE

136 Fairbank Road Clayton South, VIC 3169 (03) 9544 4222

SYDNEY

1 St James Place Seven Hills, NSW 2147 (02) 9899 6699

BRISBANE

31 South Pine Road Brendale, QLD 4500 (07) 3205 6333