

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE  
GENERATORS**

ESTABLISHED 1949

**Powermate**  
by PRAMAC

## 1kVA Powermate PMI1000

Powermate PMI series inverter: the optimal solution combining silent operation with reduced fuel consumption and tension stability. The inverter technology allows this unit to power a wide range of applications, particularly sensitive equipment such as laptops and phones.

The PMI1000 is built for maximum efficiency, with adjusting speed to match required load and inverters to reduce fuel consumption.



### FEATURES

- Inverter technology: Stable power for safe operation of sensitive electronics
- Powermate OHV engine providing consistent power for multiple applications
- Low oil level shutdown to safeguard the engine from damage
- Economy mode automatically adjusts the engine speed to the optimum level, providing excellent fuel economy and noise reduction
- USB ports to charge your mobile electronics so you can stay connected
- Lightweight and compact
- Easily transported with a handle
- Ideal for applications that require low noise

#### MELBOURNE

136 Fairbank Road  
Clayton South, VIC 3169  
(03) 9544 4222

#### SYDNEY

1 St James Place  
Seven Hills, NSW 2147  
(02) 9899 6699

#### BRISBANE

31 South Pine Road  
Brendale, QLD 4500  
(07) 3205 6333

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE  
GENERATORS**

ESTABLISHED 1949



## Specifications

<b>Model</b>	PMI1000
<b>Power</b>	Max: 1000W Rated: 900W
<b>Phase</b>	Single
<b>Fuel Type</b>	Petrol
<b>Starting System</b>	Recoil
<b>Voltage</b>	230V
<b>Engine</b>	Powermate OHV, Variable Operating Speed
<b>Fuel tank</b>	2.1L
<b>Running Time (@ 75%)</b>	5 hours
<b>Noise level (dB @ 7m)</b>	61dB
<b>Weight (kg)</b>	14kg
<b>Dimensions (L x W x H)</b>	480 x 250 x 395 mm
<b>Reference</b>	PMI1000

### MELBOURNE

136 Fairbank Road  
Clayton South, VIC 3169  
(03) 9544 4222

### SYDNEY

1 St James Place  
Seven Hills, NSW 2147  
(02) 9899 6699

### BRISBANE

31 South Pine Road  
Brendale, QLD 4500  
(07) 3205 6333