

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE  
GENERATORS**

ESTABLISHED 1949



# 12.5kVA Gentech Petrol Generator (EP12000HSRE-3)

**12.5 kVA / 3 phase portable generator powered by Honda petrol engine with electric start. Featuring 27 litre fuel tank, giving 7.11 hours of operation at 80% load.**

Builders and farmers find this generator ideal for general all-round performance with lots of grunt for welders, com-pressors and other heavy duty equipment (e.g. wool presses, and medium sized air conditioners). Featuring a 27 litre fuel tank built into the base and an electric starting system, this generator is a winner at home, on the Ute or in the shed.



## OPTIONAL ACCESSORIES

- Remote Start Pet
- DGX06: 1 axle and 2x wheels for 27 litre base tank

### MELBOURNE

136 Fairbank Road  
Clayton South, VIC 3169  
(03) 9544 4222

### SYDNEY

1 St James Place  
Seven Hills, NSW 2147  
(02) 9899 6699

### BRISBANE

31 South Pine Road  
Brendale, QLD 4500  
(07) 3205 6333

# Specifications

| Model                             | EP12000HSRE-3      |
|-----------------------------------|--------------------|
| Voltage                           | 230V/415V          |
| Power rating                      | 12.5 kVA           |
| Model rating 0.8pf@50Hz           | 12 kVA             |
| Alternator rating                 | 12.5 kVA           |
| Engine model                      | Honda V Twin GX630 |
| Phase                             | 3                  |
| Starting system                   | Electric           |
| Fuel tank capacity                | 27L                |
| Noise level @ 7m                  | 75dBA              |
| Approx fuel consumption @80% load | 3.80L/hr           |
| Operating hours @80% load         | 7.11 hr            |
| Fuel type                         | Petrol             |
| Dimensions (LWH)                  | 876 x 546 x 700 mm |
| Dry Weight                        | 130kg              |

PROUDLY 100% AUSTRALIAN OWNED

**MACFARLANE  
GENERATORS**

ESTABLISHED 1949

POWER ANYWHERE, ANYTIME!

**1300 MAC GEN (1300 622 436)**

[www.macfarlanegenerators.com.au](http://www.macfarlanegenerators.com.au)

[info@macgen.com](mailto:info@macgen.com)

## MELBOURNE

136 Fairbank Road  
Clayton South, VIC 3169  
(03) 9544 4222

## SYDNEY

1 St James Place  
Seven Hills, NSW 2147  
(02) 9899 6699

## BRISBANE

31 South Pine Road  
Brendale, QLD 4500  
(07) 3205 6333