


PROUDLY 100% AUSTRALIAN OWNED

MACFARLANE
GENERATORS



ESTABLISHED 1949



Gentech EP1600HSRE-3 Petrol Generator



Optional Accessories

- Remote Start Pet
- DGX06: 1 axle and 2x wheels for 27 litre base tank

General:

16 kVA / 3 phase portable generator powered by Honda petrol engine with electric start. Featuring 27 litre fuel tank, giving 6.59 hours of operation at 80% load.

Builders and farmers find this generator ideal for general all-round performance with lots of grunt for welders, compressors and other heavy duty equipment (e.g. wool presses, medium sized and medium sized air conditioners). Featuring a 27 litre fuel tank built into the base and an electric starting system, this generator is a winner at home, on the Ute or in the shed.

VIC Office:
136 Fairbank Road
Clayton South, VIC 3169
Tel: 03 9544 4222

NSW Office:
1 St James Place
Seven Hills, NSW 2147
Tel: 02 9899 6699

QLD Office:
31 South Pine Road
Brendale, QLD 4500
Tel: 07 3205 6333

Specifications

Power Rating	16 kVA
Model Rating 0.8pf @ 50Hz:	16 kVA
Alternator Rating:	16 kVA
Engine Model:	Honda V Twin GX690
Phase:	1-Phase/ 3-Phase
Starting System:	Electric start
Fuel Tank Capacity:	27 L
Noise Level @ 7m:	75 dBA
Volts:	230 V/ 415 V
Approx. Fuel Consumption @ 80% Load:	4.10 L/hr
Operation Hours @ 80% Load:	6.59 hr
Fuel Type:	Petrol
Dimensions:	876 x 546 x 700 mm (L x W x H)
Weight:	165 kg

Join us on Facebook



WWW.MACFARLANEGENERATORS.COM.AU